# **Spring Set Brake KFB**

















Reliable

**High Performance** 

**Easy Maintenance** 

Compact Tried and Trusted

# **Description KFB**



#### **Main Features**

Spring applied safety brake
Electromechanically released
Protection-class IP67 – seawater protected
High wear reserve by multiple air gap adjustment
Small construction at high work capacity
High availability caused by high durability
Functional without cover
Emergency release screws

#### **Applications**

Gantry, trolley and hoisting application
Dynamic and static use at general industrial applications
General engineering
Steel mills
Wind energy systems
Coal mining

#### **Certificates**

### **Options**

Special brake torque
Handlever
Micro or proximity switch:  • Monitoring the function on/off  • Maximum air gap (wear-monitoring)
Lateral junction box
Tacho preparation with all mounting parts
Cover bore
Shaft sealing
Special voltage
Anti condensation heater
Radial cable outlet
Special flange

## **Electrical equipment**

	One-way, bridge and switching rectifier									
	Protective element									
	Brake control unit	=	BCU 2001							
	Brake control and monitoring system	=	BCMS-4							



#### Please Note

We supply a detailed operating manual with every order. Nevertheless, we would point out that brakes are only as safe as the servicing and maintenance performed while they are in operation. The guarantee for the correct functioning of our brakes is only valid if the user adheres to the German DIN standard 15434 part 2 (drum and disc brakes, servicing and maintenance in operation), or to comparable standards in his own country.




#### PINTSCH BUBENZER Service


This includes the verification of the brake selection, if required. A detailed questionnaire is provided for this purpose. Installation and commissioning on-site by PINTSCH BUBENZER service engineers is possible. Drawings as DWG/DXF files for your engineering department are available upon request.

# **Spring Set Brake KFB**Electromagnetic Two Disc, Spring Set Brake



Rev. 10-09





\* The larger dimension belongs to the larger assigned brake.

Alterations reserved without notice.

Brake	KFB 5	KF 10		KFB 16	KFB 25	KF 3		KFB 40	KFB 63	KFB 100	KFB 160		
	Brake torque M2 dynamic acc. to DIN VDE 0580 Nm				0	160	250	30	00	400	630	1000	1600
	Mass moment of intertia kgm <sup>2</sup>				)17	0.0037	0.0048	0.00		0.0068	0.0175	0.036	0.050
	Mass (weight) kg				9	28	42	5		55	74	106	168
max. speed min-1  O Nominal voltage V DC			6000	600		6000	6000	60		5500	4700	4000	3600
ງ .	Nominal v	110	11	-	110	110	11		110	110	110	110	
Coil	Nominal p	79	93		128	158	13		196	220	307	344	
p.	Nominal c	0.72	8.0	_	1.16	1.44	1.		1.78	2.0	2.79	3.13	
Air gap,	Air gap, OFF norm. mm		0.3	0.		0.3	0.3	0.		0.3	0.4	0.4	0.4
		max. mm	0.8	1.0		1.0	1.2	0.		1.2	1.3	1.6	1.8
		d pilot bore	8	26		26	36	2		36	36	36	36
<u>_</u>	٥	,	15	28		28	38	3:		38	48	60	60
Diameter mm	B-Side	d <sup>H7</sup> preferrential	20 25	32		32 38	42 48	3:		42 48	55 60	65 75	65 75
iam	В-	bore	20	30	<del>}</del>	აი	55	4.		55	00	70	73
				+	-		33	+ 4	-	55			
	<u> </u>			+	$\overline{}$			+					
	е		160/200	200/	250	253/303	300/350	250/	300 ;	303/350	350/400	400/450	450/550
	f			1									
Ħ		93	106		144	194	14	4	194	214	264	314	
Lenght		110	11	0	96	117	13	37	117	142	148	155	
Le Le		110	11	0	96	117	13	37	117	142	142	142	
		145	154		141	165	17		175	187	196	218	
		13	15		15	15	1		15	15	15	17	
∢	∢ α°		22.5	30		30	30	67		30	30	30	30
			A160 A200	A20		A250	A300	A2		A300	A350	A400	A450
	Suitable standards flanges			A2:	50	A300	A350	A3	00	A350	A400	A450	A550
					-+			+					
				nsions of s									
	Size of star	A160	A200	A250	A300	A350	A400	A450	A550				
rer -		160	200	250	300	350	400	450	550				
Diameter mm	b c <sup>H7</sup>		130	165	215	265	300	350	400	500			
		110	130	180	230	250	300	350	450	1			
tg e		18	18	18/20*	20/22*	22	22/24*	24/29*	24/29*				
Lenght		5 11	5 11	5 13	5 13	6 17.5	6 17.5	6 17.5	6 17.5				
	_ r Screws k		4xM8	4xM10	4xM12		4xM16	4xM16	8xM16	8xM16	-		
Sciews K			4XIVIÖ	4XIVI I U	4XIVI I Z	4XIVI I Z	4XIVII0	4XIVI I 0	OXIVI I O	OXIVI ID			